

Xerox[®] VersaLink[®] C405 Colour Multifunction Printer

VersaLink C405 Colour Multifunction Printers are built on Xerox® ConnectKey® Technology. For more information, go to www.connectkey.com.



| System Specifications | VersaLink C405/N | VersaLink C405/DN | |
|---|--|---|--|
| One-sided Speed 8.5 x 11 in. A4 / 210 x 297 mm 8.5 x 14 in. / 216 x 356 mm | Up to 36 ppm colour and black and white Up to 35 ppm colour and black and white Up to 30 ppm colour and black and white | | |
| Two-sided Speed 8.5 x 11 in. A4 / 210 x 297 mm 8.5 x 14 in. / 216 x 356 mm | NA | Up to 24 ppm colour and black and white Up to 23 ppm colour and black and white Up to 21 ppm colour and black and white | |
| Monthly Duty Cycle ¹ | Up to 80,000 pages / month ¹ | | |
| Recommended Average Monthly Print Volume ² | Up to 5,000 pages | | |
| Processor | 1.05 GHz Dual-Core | | |
| Memory | 2 GB | | |
| Connectivity | Ethernet 10/100/1000 Base-T, High-speed USB 3.0, Wi-Fi 802.11n and Wi-Fi Direct with optional Wi-Fi Kit (concurrent wired and wireless connections supported), NFC Tap-to-Pair | | |
| Controller Features | Unified Address Book, Configuration Cloning, Scan Preview, Xerox Extensible Interface Platform®, Xerox App Gallery, Xerox® Standard Accounting, Network Accounting Enabled, Role Based Permissions, Convenience Authentication Enabled, Online Support (accessed from the user interface and print driver) | | |
| User Interface Languages | English, French, Italian, German, Spanish, Brazilian Portuguese, Russian, Dutch, Swedish, Danish, Finnish, Norwegian, Greek, Turkish, Polish, Czech, Hungarian, Romanian, Catalan, Ukrainian, Croatian | | |
| Device Specifications | | | |
| Electrical Requirements | | | |
| North America | Voltage: 110-127 VAC+/- 10 % Frequency: 50/60 Hz+/- 3Hz, 10 A | | |
| Europe and Other Geographies | Voltage: 220-240 VAC+/- 10 % Frequency: 50/60 Hz+/- 3Hz, 6 A | | |
| Power Consumption | | | |
| Continuous Printing ³ | 750 watts or less | | |
| Ready / Standby Mode ³ | 82 watts or less | | |
| Energy Saver / Sleep Mode ³ | 4 watts or less | | |

| Operating Environment | | | | |
|---|--|--------------------------------|-------------------|-------------------|
| Required Temperature Range (Storage) | 32° F to 95° F / 0° C to 3 | 32° F to 95° F / 0° C to 35° C | | |
| Required Temperature Range (Operating) | 50° F to 90° F / 10° C to | 32° C | | |
| Required Relative Humidity | 10 % to 85 % | | | |
| Sound Power Levels Operating Standby | 6.88 B(A) or less 5.0 B(A) or less | | | |
| Sound Pressure Levels Operating Standby | 52.3 dB(A) or less 28.7 dB(A) or less | | | |
| Boot Time (from Off to UI Ready) | As fast as 60 seconds | | | |
| Warm-up Time (from Sleep to UI Ready) | As fast as 6 seconds | | | |
| Dimensions and Weight (Unpackaged) | Width | Depth | Height | Weight |
| VersaLink C405N and DN | 17 in. / 432 mm | 21.3 in. / 540 mm | 23.6 in. / 599 mm | 72 lb. / 33 kg |
| 550-sheet Paper Tray | 16.8 in. / 427 mm | 19.1 in. / 485 mm | 5.4 in. / 138 mm | 8.6 lb. / 3.9 kg |
| Dimensions and Weight (Packaged) | Width | Depth | Height | Weight |
| VersaLink C405N and DN | 23.7 in. / 602 mm | 26.3 in. / 669 mm | 30.0 in. / 761 mm | 86 lb. / 39 kg |
| 550-sheet Paper Tray | 23.2 in. / 590 mm | 21.4 in. / 544 mm | 9.5 in. / 241 mm | 11.7 lb. / 5.3 kg |
| System Certification/Regulatory C | Compliance | | | |
| Certifications | To view the latest list of certifications, go to www.xerox.com/OfficeCertifications. | | | |
| Print | nt | | | |
| First-print-out Time | As fast as 13 seconds colour / 12 seconds black and white | | | |
| Print Resolution | Up to 600 x 600 x 8 dpi (enhanced) | | | |
| Page Description Languages | PCL® 5e, 6 PDF XPS TIFF JPEG HP-GL Adobe® PostScript® 3™ | | | |
| Maximum Print Area | 4 mm from edge of paper | | | |

| Print Features Application Defaults Banner Pages Enable / Disable Bi-directional Real-time Status Booklet Layout Drift Mode Fit to new pager size Job Identification Print ID or Banner, Print ID in margins on first page only or all pages) Society Print Print | | | |
|--|---|--|--|
| Supports direct printing from computer via Type B USB port Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A Windows 9.7, 8, 8.1, 10 Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016 macOSo 10.11, 10.12, 10.13 Citrix® Redhat® Enterprise Linux® Fedora Core IBM® AIX® HP-UX® Oracle® Solaris SUSE® Note: For information about supported versions for the above operating systems, please visit our Drivers & Downloads page and specify your device at www.support.xerox.com. Fonts PostScript fonts: 136 PCL fonts: 83 Xerox® Mobile Express Driver® Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location. Plug linto a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of "favorite" printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to TT. A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end- users, reducing the number of support calls, and simplifying print services management. Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print Driver Makes it easy for IT managers to qualify, deploy and manage all print devices wising a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver with a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver water devices from a single driver. Uses a single queue and single driver. The Xerox® Pull Print Driver water devices from a single driver. Uses a single queue and single driver. The Xerox® Pull Print Driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver water devices from a single dri | Print Features | Banner Pages Enable / Disable Bi-directional Real-time Status Booklet Layout Draft Mode Fit to new paper size Job Identification (Print ID or Banner, Print ID in margins on first page only or all pages) Job Monitoring (Client or Local User Interface) LAN Fax (requires Fax Kit) N-up Page Layout (up to 16 pages per sheet) Paper Selection by Attribute Personal Print Print Around Enable / Disable Print from USB Sample Set Saved Job Scaling Secure Print Skip Blank Pages Special Pages (exception page programming: covers, inserts, exceptions pages) Stored Jobs Deletion Two-sided Printing (as default) Watermark (predefined and custom) | |
| Windows Server 2008 8P2, Server 2012, Server 2012 R2, Server 2016 macOS® 10.11, 10.12, 10.13 Citrix® Redhat® Enterprise Linux® Redhat® Enterprise Linux® Fedora Core IBM® AIX® HP-UJ® Oracle® Solaris SUSE® SAP® Note: For information about supported versions for the above operating systems, please visit our Drivers & Downloads page and specify your device at www.support.xerox.com. Fonts PostScript fonts: 136 PCL fonts: 83 Xerox® Mobile Express Driver® Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location, Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of "favorite" printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to 1T. Xerox® Global Print Driver® A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for endusers, reducing the number of support calls, and simplifying print services management. Xerox® Pull Print Driver Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others. Copy Document Scanner 50-sheet Single-Pass Duplex Automatic Document Feeder (DADF) Document Scanner Size DADF: Up to 8.5 x 11.7 in. / AA DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 in. / A5 DADF: Up to 8.5 x 11.7 i | Print from USB | Supports direct printing from computer via Type B USB port | |
| PCL fonts: 83 | Operating Systems | Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016 macOS® 10.11, 10.12, 10.13 Citrix® Redhat® Enterprise Linux® Fedora Core IBM® AIX® HP-UX® Oracle® Solaris SUSE® SAP® Note: For information about supported versions for the above operating systems, please visit our | |
| new location. Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of "favorite" printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT. Xerox® Global Print Driver® A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for endusers, reducing the number of support calls, and simplifying print services management. Xerox® Pull Print Driver Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others. Copy Document Scanner 50-sheet Single-Pass Duplex Automatic Document Feeder (DADF) Document Scanner Size Platen: Up to 8.5 x 11.7 in. / A4 DADF: Up to 8.5 x 14 in. / 216 x 356 mm Simplex Copy Speed Up to 36 cpm (copies per minute) 8.5 x 11 in. | Fonts | | |
| non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for endusers, reducing the number of support calls, and simplifying print services management. Xerox® Pull Print Driver Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others. Copy Document Scanner 50-sheet Single-Pass Duplex Automatic Document Feeder (DADF) Platen: Up to 8.5 x 11.7 in. / A4 DADF: Up to 8.5 x 14 in. / 216 x 356 mm Simplex Copy Speed Up to 36 cpm (copies per minute) 8.5 x 11 in. | Xerox [®] Mobile Express Driver [®] | new location. Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of "favorite" printers for each location, store application print settings for use on any printer in any network, and greatly reduce | |
| in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others. Copy Document Scanner 50-sheet Single-Pass Duplex Automatic Document Feeder (DADF) Document Scanner Size Platen: Up to 8.5 x 11.7 in. / A4 | Xerox® Global Print Driver® | non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end- | |
| Document Scanner 50-sheet Single-Pass Duplex Automatic Document Feeder (DADF) Document Scanner Size Platen: Up to 8.5 x 11.7 in. / A4 DADF: Up to 8.5 x 14 in. / 216 x 356 mm Simplex Copy Speed Up to 36 cpm (copies per minute) 8.5 x 11 in. | Xerox® Pull Print Driver | in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, | |
| Document Scanner Size Platen: Up to 8.5 x 11.7 in. / A4 DADF: Up to 8.5 x 14 in. / 216 x 356 mm Simplex Copy Speed Up to 36 cpm (copies per minute) 8.5 x 11 in. | Сору | | |
| DADF: Up to 8.5 x 14 in. / 216 x 356 mm Simplex Copy Speed Up to 36 cpm (copies per minute) 8.5 x 11 in. | Document Scanner | 50-sheet Single-Pass Duplex Automatic Document Feeder (DADF) | |
| | Document Scanner Size | | |
| | Simplex Copy Speed | Up to 36 cpm (copies per minute) 8.5 x 11 in. Up to 35 cpm A4 / 210 x 297 mm | |

| Duplex Copy Speed | Up to 24 cpm (copies per minute) 8.5 x 11 in. Up to 23 cpm A4 / 210 x 297 mm | |
|---|--|--|
| First-copy-out Time | As fast as 11 seconds colour / 8 seconds black and white | |
| Sides (input:output) | 1:1, 1:2, 2:2 and 2:1 | |
| Quantity | 1 to 999 | |
| Resolution (max.) | Up to 600 x 600 dpi | |
| Reduction / Enlargement | Variable zoom from 25 % to 400 % in 1 % increments | |
| Concurrency | Concurrent scanning and printing | |
| Copy Features | Annotation (Page Numbers, Comments, Date Stamp, Bates Stamping)* Auto-color Sensing Automatic Background Suppression Book Copying with Center Erase Booklet Copying* Collation Color Balance Color Effects Darkness Control Edge Erase Front Cover ID Card Copy Image Enhancement Lighten/Darken N-up Reduce / Enlarge 25 % to 400 % Image Shift Original Orientation Original Size Original Type Page Layout Sample Copy Saturation Sharpness | |
| | *Requires HDD/Productivity Kit | |
| Scan | | |
| Capability | Black and white and colour scanning | |
| Concurrency | Scan while the system is printing copy or network print jobs, or while it is transferring scan to network or fax jobs | |
| Simplex Input Speed | Black and White: Scan up to 40 ipm – 8.5 x 11 in. / 38 ipm A4 / 210 x 297 mm Colour: Scan up to 21 ipm – 8.5 x 11 in. / 20 ipm A4 / 210 x 297 mm | |
| Duplex Input Speed | Black and White: Scan up to 52 ipm – 8.5 x 11 in. / 50 ipm A4 / 210 x 297 mm Colour: Scan up to 27 ipm – 8.5 x 11 in. / 26 ipm A4 / 210 x 297 mm | |
| Resolution | Optical – 600 x 600 dpi | |
| Bit Depth | 24-bit colour / 8-bit grayscale | |
| Maximum Scan Area | Platen: Up to 8.5 x 11.7 in. / A4 / 210 x 297 mm Document Feeder: Up to 8.5 x 14 in. / 216 x 356 mm | |
| Network Filing Protocols | FTP SMTP SMB | |
| File Formats | JPG TIFF (single and multi-page) XPS (single and multi-page) PDF (single and multi-page) PDF (single and multi-page) Searchable PDF via Optical Character Recognition (OCR) Password-protected PDF Linearised PDF (set via embedded web server) and PDF/A | |
| Scan Driver Compatibility (Network Only) | WIA TWAIN | |
| | | |

| Supported Scan Destinations | Scan to Home Scan to USB Scan to Email Scan to Network (Browse FTP or Browse SMB) | |
|---|--|--|
| Network Scanning – Software Sol | utions | |
| Xerox [®] ConnectKey [®] Apps (Found at the Xerox [®] App Gallery) | Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, serverless ConnectKey Apps to the ConnectKey-enabled device. | |
| Fax | | |
| Fax ⁴ | | |
| Fax Speed | 33.6 Kbps | |
| Memory | 4 MB | |
| Resolution | Standard 200x100 dpi, Fine 200x200 dpi, Super Fine 300x300, 400x400, 600x600 dpi | |
| Compression | MH, MR, MMR, JBIG | |
| Fax Features | Walk-up Fax, LAN Fax, Direct Fax, Fax Forward to Email Fax dialing via Unified Address Book (up to 2,000 contacts) | |
| Mobile Solutions and Mobile Devi | ce Apps | |
| Apple [®] AirPrint [®] | Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network. | |
| Google Cloud Print™ | Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other webconnected device. | |
| @PrintByXerox | @PrintByXerox is a free service that allows secure printing from any email-enabled device (computer, phone, tablet, iOS, Android™, Google® Chromebook™ and more) to a Xerox® printer or MFP using a single email address with no IT intervention. No training is needed. End-users simply send attachments to the email address, and release them at the MFP panel. | |
| Xerox [®] Print Service Plug-in for Android™ (Free αt Google Play™ Store) | The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to printers or multifunction printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store. | |
| Xerox® Mobile Link App (Free at Google Play™ Store and Apple® App Store) | The Xerox® Mobile Link App allows you to scan, email and fax from your phone or tablet by connecting with our multifunction printers and send data to and print data from cloud storage. It is easy to create Mobile Link One-Touch Workflows between a mobile device and a multifunction printer. Using a manual address or QR code identification for pairing, automatic device discovery makes it easy to find and pair a mobile device with a nearby Xerox® multifunction printer. | |
| Xerox® Print Management and Mobility Suite, Xerox® Print Management and Mobility Service | Xerox® Print Management and Mobility Suite is a modular set of workflows designed to save customers time and money by providing effective control over their print fleet, while enabling worker productivity and mobility through a set of robust workflows. Xerox enables ultimate customer flexibility by offering these capabilities in both an on-premises server version and with a cloud based-version of this solution. | |

| Security | | |
|---|---|--|
| Security Features | Access Controls AES 256-bit Encryption Audit Log Certificate Path Validation Certificate Revocation List (CRL)/Status Protocol (OCSP) Detection of external program falsification (XCP Plug-in) Cisco® Identity Services Engine (ISE) Integration Domain Filtering FIPS 140-2 Firmware Verification Immediate Disk Overwrite* IP Address Filtering IPsec Network Authentication Port Filtering Pre-installed Self-Signed Certificates Role Based Permissions Secure Email Secure Fax Secure Print Security Certificate Management Smart Card Enablement (CAC/PIV/.NET) SNMPv3 Status Protocol (OCSP) TLS/SSL *Requires HDD/Productivity Kit | |
| Assounting | Requires FIDD/FIOductivity Kit | |
| Accounting Xerox® Standard Accounting Tool | / Naturally Accounting (Standard) | |
| Tracking | - | |
| Accounting | Copy, Print, Fax, Scan and Email usage Xerox® Standard Accounting Tool | |
| | Up to 1,000 User Accounts without HDD Up to 9,999 User Accounts with HDD Up to 500 General accounts Network Accounting (Job Based Accounting) Up to 1,000 User IDs; Up to 1,000 Account IDs without HDD Up to 60,000 User IDs; Up to 60,000 Account IDs with HDD Up to 14,000 accounting records (transactions) | |
| Features | Administrator can manage the feature via the Embedded Web Server. | |
| Accounting Options – Network Ac | counting (Allows central server to manage all accounting) | |
| | Enhanced network accounting with up to the minute data on how the system is being used Comprehensive management and enterprise scale tracking and reporting of device usage Numerous solutions are available through Xerox Alliance Partners. For details visit www.xerox.com Security enhancements include simultaneous support for HTTP/HTTPS protocols Device requests account authentication from third party server enabling larger databases of users and accounts Accept Authentication Login at control panel and pass to third party Networking Account | |
| Paper Handling | | |
| Document Feeder | | |
| Capacity ⁵ | Single-Pass Duplex Automatic Document Feeder (DADF): 50 sheets | |
| Sizes | Custom Sizes: 5.5 x 5.5 in. to 8.5 x 14 in. / 139.7 x 139.7 mm to 216 x 356 mm | |
| Weights One-sided: Two-sided: | 13 lb. bond to 45 lb. cover / 50 to 125 gsm 16 lb. bond to 45 lb. cover / 60 to 125 gsm | |
| Bypass Tray | | |
| Capacity ⁵ | 150 sheets | |
| Sizes | Custom Sizes: 3 x 5 in. to 8.5 x 14 in. / 76.2 x 127 mm to 216 x 356 mm | |

| Weights One-sided: Two-sided: | 16 lb. bond to 80 lb. cover / 60 to 220 gsm 16 lb. bond to 60 lb. cover / 60 to 163 gsm |
|---------------------------------------|---|
| Types | Plain Lightweight Cardstock Cardstock Hole Punched Recycled Pre-Printed Letterhead Bond Lightweight Glossy Cardstock Glossy Cardstock Labels Envelopes Custom |
| Tray 1 | |
| Capacity ⁵ | 550 sheets |
| Sizes | Custom sizes: 5.8 x 8.3 in. to 8.5 x 14 in. / 148 x 210 mm to 216 x 356 mm |
| Weights One-sided: Two-sided: | 16 lb. bond to 80 lb. cover / 60 to 220 gsm 16 lb. bond to 60 lb. cover / 60 to 163 gsm |
| Types | Plain Lightweight Cardstock Cardstock Hole Punched Recycled Pre-Printed Letterhead Bond Lightweight Glossy Cardstock Glossy Cardstock Custom |
| Optional Tray 2 | |
| Capacity ⁵ | 550 sheets |
| Sizes | Custom sizes: 5.8 x 8.3 in. to 8.5 x 14 in. / 148 x 210 mm to 216 x 356 mm |
| Weights One-sided: Two-sided: | 16 lb. bond to 80 lb. cover / 60 to 220 gsm 16 lb. bond to 60 lb. cover / 60 to 163 gsm |
| Types | Plain Lightweight Cardstock Cardstock Hole Punched Recycled Pre-Printed Letterhead Bond Lightweight Glossy Cardstock Glossy Cardstock Custom |
| Total Capacity | |
| Standard Device Capacity ⁵ | 700 sheets |
| Total Device Capacity ⁵ | 1,250 sheets |
| Paper Output | |
| Output Capacity ⁵ | 250 sheets |
| Automatic Two-sided Printing | VersaLink C405N: NA VersaLink C405DN: Standard |

| Device Management | | | |
|---|--|--|--|
| Network Protocols | TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD LDAP Bonjour® / AirPrint™ FTP Most protocols not in use can be disabled | | |
| Administrative Protocols | DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS | | |
| Xerox® CentreWare® Web Softwa | | | |
| | A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system Works with any SNMP-managed printer from any manufacturer Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management | | |
| Xerox [®] Embedded Web Server – 1 | Integrated Device Web Page | | |
| Device Status | Tray status/contents Consumables status Billing/Usage Quick Links Online Support | | |
| Print Queue Viewing | Job print queue management—view and delete | | |
| Job Submission | Print-ready files (PS, PCL, PDF, XPS, JPEG) | | |
| Device Administration | Allows simple, remote installation setting of configuration options and management of the device | | |
| Browsers | Microsoft® Internet Explorer® Microsoft Edge™ Mozilla™ Firefox® Apple® Safari® Google Chrome™ | | |
| Remote Services | | | |
| Xerox® Meter Assistant® Service | Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time. | | |
| Xerox [®] Supplies Assistant [®] Service | Automatically orders supplies for Xerox® output devices based on actual usage, eliminating the need to manually manage supplies inventory. | | |
| MaintenanceAssistant | Offers a fast (and free) way to resolve potential issues and receive assistance and automate the troubleshooting/repair process. Diagnostic data is sent to Xerox, allowing for problems to be solved faster with increased uptime. | | |
| What's In The Box | | | |
| | VersaLink C405 Colour Multifunction Printer Starter Capacity Print Cartridge: One of each (Cyan, Magenta, Yellow: 2,000 print capacity ⁶ , Black: 3,000 print capacity ⁶ Software and Documentation CD (Safety, Regulatory, Recycling and Disposal Guides, Print Drivers, and Warranty Statement) Installation Guide Quick Use Guides Power cord Fax cord | | |

| Supplies and Accessories | Quantity | Part Number | |
|---|--|--|--|
| Supplies | | | |
| Standard Capacity Print Cartridges | Cyan: 2,500 standard pages ⁶ Magenta: 2,500 standard pages ⁶ Yellow: 2,500 standard pages ⁶ Black: 2,500 standard pages ⁶ | 106R03510 106R03511 106R03509 106R03508 | |
| High Capacity Print Cartridges | Cyan: 4,800 standard pages ⁶ Magenta: 4,800 standard pages ⁶ Yellow: 4,800 standard pages ⁶ Black: 5,000 standard pages ⁶ | 106R03522 106R03523 106R03521 106R03520 | |
| Extra High Capacity Print Cartridges | Cyan: 8,000 standard pages ⁶ Magenta: 8,000 standard pages ⁶ Yellow: 8,000 standard pages ⁶ Black: 10,500 standard pages ⁶ | 106R03534 106R03535 106R03533 106R03532 | |
| Routine Maintenance Items | | | |
| Imaging Unit (includes 4 imaging units) | Cyan: 60,000 standard pages ⁷ Magenta: 60,000 standard pages ⁷ Yellow: 60,000 standard pages ⁷ Black: 60,000 standard pages ⁷ | 108R01121 | |
| Waste Cartridge | 30,000 standard pages ⁷ | 108R01124 | |
| Accessories | | | |
| 550-sheet Paper Tray | | 097S04400 | |
| Productivity Kit with 320 GB HDD | | 097S04914 | |
| Stand | | 497K13660 | |
| Wireless Network Adapter | | 497K16750 | |
| Internal Card Reader / RFID Kit | | 497K18120 | |

Return spent imaging supplies through the Xerox Green World Alliance collection/reuse/recycling programme. For more information, visit www.xerox.com/about-xerox/recycling.

For more information, visit us at www.xerox.com/office

Configurations vary by geography.



¹ Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.
2 Expected regular monthly throughput.
3 Power states defined per ENERGY STAR® Programme requirements for Imaging Equipment.
4 Requires analogue phone line.
5 Paper capacities are based on 20 lb. / 75 gsm stock; capacities will vary with different weight stocks.
6 Average standard pages. Declared Yield in accordance with ISO/IEC 19798. Yield will vary based on image, area coverage and print mode.
7 Approximate pages. Declared yield will vary depending on job run length, media size/orientation and machine speed. For more information visit: http://www.office.xerox.com/latest/SUPGL-01.pdf.